DMX CHART

Martin Atomic 3000

Prepared by Krank'd · krankd.com.au

Hire this fixture from Krank'd

1ch 3ch 4ch

1-Channel DMX Mode

1CH	VALUE	FUNCTION
1		**Flash rate / blinder**
	000–005	Blackout
	006–249	Flash rate, slow to fast
	250–255	Continuous "Blinder" effect

3 and 4 Channel DMX Modes

3CH	4CH	VALUE	FUNCTION
1	1		**Flash intensity**
		000–005	Blackout
		006–255	Minimum to maximum
2	2	000–255	**Flash duration** · 0–650 ms @ 50 Hz AC, or 0–530 ms @ 60 Hz AC
3	3		**Flash rate**
		000–005	No flash (single flash with ch. 1)
		006–255	0.5–25 Hz @ 50 Hz AC, or 0.6–30 Hz @ 60 Hz AC
·	4		**Special effects**
		000–005	No effect
		006–042	Ramp up
		043–085	Ramp down
		086–128	Ramp up-down
		129–171	Random
		172–214	Lightning
		215–255	Spikes

※ Channel 4 (Special effects) is enabled with Mode DIP switch no. 4 on; it is present only in 4-channel mode.