DMX CHART

ACME Stage Par Colour

Model BL-100 RGBW · Prepared by Krank'd · krankd.com.au

Hire this fixture from Krank'd

6ch 7ch HSIC 4ch

6 Channel Mode

6CH	VALUE	FUNCTION
1	000-255	**R** · Dimmer 0 → 100%
2	000-255	**G** · Dimmer 0 → 100%
3	000-255	**B** · Dimmer 0 → 100%
4	000-255	**W** · Dimmer 0 → 100%
5	000-255	**Total Dimmer** · Total Dimmer 0 → 100%
6		**Flash**
	000-005	Open
	006-123	Flash Rate, slow to fast
	124-127	Open
	128-168	LED random strobe (speed1)
	169-208	LED random strobe (speed2)
	209-249	LED random strobe (speed3)
	250-255	Open

7 Channel Mode

7CH	VALUE	FUNCTION
1	000-255	**R** · Dimmer 0 → 100%
2	000-255	**G** · Dimmer 0 → 100%
3	000-255	**B** · Dimmer 0 → 100%
4	000-255	**W** · Dimmer 0 → 100%
5		**Color**
	000-007	NO effect
	008-015	LEE790 - Moroccan pink
	016-022	LEE157 - Pink
	023-030	LEE332 - Special rose pink
	031-037	LEE328 - Follies pink
	038-045	LEE345 - Fuchsia pink
	046-052	LEE194 - Surprise pink
	053-060	LEE181 - Congo Blue
	061-067	LEE071 - Tokyo Blue
	068-075	LEE120 - Deep Blue
	076-082	LEE079 - Just Blue
	083-090	LEE132 - Medium Blue
	091-097	LEE200 - Double CT Blue
	098-105	LEE161 - Slate Blue
	106-112	LEE201 - Full CT Blue

7CH	VALUE	FUNCTION
	113-120	LEE202 - Half CT Blue
	121-127	LEE117 - Steel Blue
	128-135	LEE353 - Lighter Blue
	136-142	LEE118 - Light Blue
	143-150	LEE116 - Medium Blue Green
	151-157	LEE124 - Dark Green
	158-165	LEE139 - Primary Green
	166-172	LEE089 - Moss Green
	173-180	LEE122 - Fern Green
	181-187	LEE738 - JAS Green
	188-195	LEE088 - Lime Green
	196-202	LEE100 - Spring Yellow
	203-210	LEE104 - Deep Amber
	211-217	LEE179 - Chrome Orange
	218-225	LEE105 - Orange
	226-232	LEE021 - Gold Amber
	233-240	LEE778 - Millennium Gold
	241-247	LEE135 - Deep Golden Amber
	248-255	LEE164 - Flame Red
6	000-255	**Total Dimmer** · Total Dimmer 0 → 100%
7		**Flash**
	000-005	Open
	006-123	Flash Rate, slow to fast
	124-127	Open
	128-168	LED random strobe (speed1)
	169-208	LED random strobe (speed2)
	209-249	LED random strobe (speed3)
	250-255	Open

HSIC Channel Mode

HSIC	VALUE	FUNCTION
1		**Color**
	000-007	Red
	008-015	Orange
	016-079	Orange → Green
	080-087	Green
	088-159	Green → Blue
	160-167	Blue
	168-239	Blue → Red
	240-255	Red
2	000-255	**Saturation** · White → The color of the 1 channel
3	000-255	**Dimmer** · Dimmer 0 → 100%

HSIC	VALUE	FUNCTION
4		**Color temperature**
	000-008	NO effect
	009-255	2000K → 10000K

4 Channel Mode (BL-100 RGBW only)

4CH	VALUE	FUNCTION
1	000-255	**R** · Dimmer 0 → 100%
2	000-255	**G** · Dimmer 0 → 100%
3	000-255	**B** · Dimmer 0 → 100%
4	000-255	**W** · Dimmer 0 → 100%

※ HSIC channel 1 (Color) is a continuous hue wheel; the source labels only the anchor hues (Red, Orange, Green, Blue, Red) and shows transition dots for the bands between them. Those bands are listed as the blend between the named hues either side.

※ The 4Channel Mode is printed with the note "Only BL-100 RGBW is available"; this fixture is the BL-100 RGBW, so the mode applies.

※ Source misprints corrected per the LEE filter catalogue: 'State Blue' → 'Slate Blue' (LEE 161), 'Deep Gold Amber' → 'Deep Golden Amber' (LEE 135).