DMX CHART

ACME Super Dot Line

Model TB 1060 · Prepared by Krank'd · krankd.com.au

Hire this fixture from Krank'd

17ch | 27ch | 99ch | 108ch | 168ch | 8+100ch (Mode 6) | 8+160ch (Mode 7) | 8+100ch Art-Net (Mode 6) | 8+160ch Art-Net (Mode 7) | 21ch

Mode 1-5 (17ch / 27ch / 99ch / 108ch / 168ch)

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
1	1	1	1	1	000-255	**Tilt** · 0° → 202°
2	2	2	2	2	000-255	**Tilt Fine**
3	3	3	3	3	000-255	**Zoom** · Wide → Narrow
4	4	4	4	4	000-255	**Dimmer** · 0% → 100%
5	5	5	5	5		**Main Strobe**
					000-007	Close
					008-015	Open
					016-131	Strobe from Slow to Fast
					132-139	Open
					140-181	Slow Open Fast Close from Slow to Fast
					182-189	Open
					190-231	Fast Open Slow Close from Slow to Fast
					232-239	Open
					240-247	Random Strobe from Slow to Fast
					248-255	Open
6	6	6	6	6		**Line_W Strobe**
					000-007	Close
					008-015	Open
					016-131	Strobe from Slow to Fast
					132-139	Open
					140-181	Slow Open Fast Close from Slow to Fast
					182-189	Open
					190-231	Fast Open Slow Close from Slow to Fast
					232-239	Open
					240-247	Random Strobe from Slow to Fast
					248-255	Open
7	7	7	7	7		**Line_RGB Strobe**
					000-007	Close
					008-015	Open
					016-131	Strobe from Slow to Fast
					132-139	Open
					140-181	Slow Open Fast Close from Slow to Fast
					182-189	Open
					190-231	Fast Open Slow Close from Slow to Fast

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
					232-239	Open
					240-247	Random Strobe from Slow to Fast
					248-255	Open
8	8	8	8	8		**Special Function**
					000-029	Null
					030-039	Dimmer Curve: Linear
					040-049	Dimmer Curve: Square Law
					050-059	Dimmer Curve: Inv SQ Law
					060-069	Dimmer Curve: S Curve
					070-079	Power Mode: Standard
					080-089	Null
					090-099	Power Mode: Quiet
					100-109	Led Frequency Setting Enable
					110-119	Led Frequency Setting Disable
					120-122	Null
					123	900Hz
					124	1000Hz
					125	1100Hz
					126	1200Hz
					127	1300Hz
					128	1400Hz
					129	1500Hz
					130	2500Hz
					131	4000Hz
					132	5000Hz
					133	6000Hz
					134	10KHz
					135	15KHz
					136	20KHz
					137	25KHz
					138-139	Null
					140-149	Tilt Reset
					150-159	Effect Reset
					160-169	CCT Calibration: On
					170-179	CCT Calibration: Off
					180-189	Invert Pixel Order: No
					190-199	Invert Pixel Order: Yes
					200-209	All Reset
					210-219	Dimmer Speed: Fast
					220-229	Dimmer Speed: Smooth
					230-239	Line Power Mode: Off

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
					240-249	Line Power Mode: On
					250-251	Dimming Start Mode: High
					252-253	Dimming Start Mode: Low
					254-255	Null
9	9	·	·	·	000-255	**Main Red** · 0% → 100%
10	10	·	·	·	000-255	**Main Green** · 0% → 100%
11	11	·	·	·	000-255	**Main Blue** · 0% → 100%
12	12	·	·	·	000-255	**Main White** · 0% → 100%
·	·	9	9	9	000-255	**Main Red 1** · 0% → 100%
·	·	10	10	10	000-255	**Main Green 1** · 0% → 100%
·	·	11	11	11	000-255	**Main Blue 1** · 0% → 100%
·	·	12	12	12	000-255	**Main White 1** · 0% → 100%
·	·	13	13	13	000-255	**Main Red 2** · 0% → 100%
·	·	14	14	14	000-255	**Main Green 2** · 0% → 100%
·	·	15	15	15	000-255	**Main Blue 2** · 0% → 100%
·	·	16	16	16	000-255	**Main White 2** · 0% → 100%
·	·	17	17	17	000-255	**Main Red 3** · 0% → 100%
·	·	18	18	18	000-255	**Main Green 3** · 0% → 100%
·	·	19	19	19	000-255	**Main Blue 3** · 0% → 100%
·	·	20	20	20	000-255	**Main White 3** · 0% → 100%
·	·	21	21	21	000-255	**Main Red 4** · 0% → 100%
·	·	22	22	22	000-255	**Main Green 4** · 0% → 100%
·	·	23	23	23	000-255	**Main Blue 4** · 0% → 100%
·	·	24	24	24	000-255	**Main White 4** · 0% → 100%
·	·	25	25	25	000-255	**Main Red 5** · 0% → 100%
·	·	26	26	26	000-255	**Main Green 5** · 0% → 100%
·	·	27	27	27	000-255	**Main Blue 5** · 0% → 100%
·	·	28	28	28	000-255	**Main White 5** · 0% → 100%
·	·	29	29	29	000-255	**Main Red 6** · 0% → 100%
·	·	30	30	30	000-255	**Main Green 6** · 0% → 100%
·	·	31	31	31	000-255	**Main Blue 6** · 0% → 100%
·	·	32	32	32	000-255	**Main White 6** · 0% → 100%
·	·	33	33	33	000-255	**Main Red 7** · 0% → 100%
·	·	34	34	34	000-255	**Main Green 7** · 0% → 100%
·	·	35	35	35	000-255	**Main Blue 7** · 0% → 100%
·	·	36	36	36	000-255	**Main White 7** · 0% → 100%
·	·	37	37	37	000-255	**Main Red 8** · 0% → 100%
·	·	38	38	38	000-255	**Main Green 8** · 0% → 100%
·	·	39	39	39	000-255	**Main Blue 8** · 0% → 100%
·	·	40	40	40	000-255	**Main White 8** · 0% → 100%

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
·	·	41	41	41	000–255	**Main Red 9** · 0% → 100%
·	·	42	42	42	000–255	**Main Green 9** · 0% → 100%
·	·	43	43	43	000–255	**Main Blue 9** · 0% → 100%
·	·	44	44	44	000–255	**Main White 9** · 0% → 100%
·	·	45	45	45	000–255	**Main Red 10** · 0% → 100%
·	·	46	46	46	000–255	**Main Green 10** · 0% → 100%
·	·	47	47	47	000–255	**Main Blue 10** · 0% → 100%
·	·	48	48	48	000–255	**Main White 10** · 0% → 100%
·	13	·	·	·		**Main CCT**
					000	Null
					001–004	8000K
					005–009	7900K
					010–013	7800K
					014–018	7700K
					019–022	7600K
					023–027	7500K
					028–031	7400K
					032–036	7300K
					037–040	7200K
					041–045	7100K
					046–049	7000K
					050–054	6900K
					055–058	6800K
					059–063	6700K
					064–067	6600K
					068–072	6500K
					073–076	6400K
					077–081	6300K
					082–085	6200K
					086–090	6100K
					091–094	6000K
					095–099	5900K
					100–103	5800K
					104–108	5700K
					109–112	5600K
					113–117	5500K
					118–121	5400K
					122–126	5300K
					127–130	5200K
					131–135	5100K
					136–139	5000K

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
					140-144	4900K
					145-148	4800K
					149-153	4700K
					154-157	4600K
					158-162	4500K
					163-166	4400K
					167-171	4300K
					172-175	4200K
					176-180	4100K
					181-184	4000K
					185-189	3900K
					190-193	3800K
					194-198	3700K
					199-202	3600K
					203-207	3500K
					208-211	3400K
					212-216	3300K
					217-220	3200K
					221-225	3100K
					226-229	3000K
					230-234	2900K
					235-238	2800K
					239-243	2700K
					244-247	2600K
					248-255	2500K
	14					**Main Color**
					000-007	Null
					008-015	Color 1
					016-023	Color 2
					024-031	Color 3
					032-039	Color 4
					040-047	Color 5
					048-055	Color 6
					056-063	Color 7
					064-071	Color 8
					072-079	Color 9
					080-087	Color 10
					088-095	Color 11
					096-103	Color 12
					104-111	Color 13
					112-119	Color 14

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
					120-127	Color 15
					128-135	Color 16
					136-143	Color 17
					144-151	Color 18
					152-159	Color 19
					160-167	Color 20
					168-175	Color 21
					176-183	Color 22
					184-191	Color 23
					192-199	Color 24
					200-207	Color 25
					208-215	Color 26
					216-223	Color 27
					224-231	Color 28
					232-239	Color 29
					240-247	Color 30
					248-255	Color 31
	15					**Main Macro**
					000-007	Null
					008-015	Built-in Effect 1
					016-023	Built-in Effect 2
					024-031	Built-in Effect 3
					032-039	Built-in Effect 4
					040-047	Built-in Effect 5
					048-055	Built-in Effect 6
					056-063	Built-in Effect 7
					064-071	Built-in Effect 8
					072-079	Built-in Effect 9
					080-087	Built-in Effect 10
					088-095	Built-in Effect 11
					096-103	Built-in Effect 12
					104-111	Built-in Effect 13
					112-119	Built-in Effect 14
					120-127	Built-in Effect 15
					128-135	Built-in Effect 16
					136-143	Built-in Effect 17
					144-151	Built-in Effect 18
					152-159	Built-in Effect 19
					160-167	Built-in Effect 20
					168-175	Built-in Effect 21
					176-183	Built-in Effect 22

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
					184-191	Built-in Effect 23
					192-199	Null
					200-207	Null
					208-215	Null
					216-223	Null
					224-231	Null
					232-239	Null
					240-247	Null
					248-255	Null
·	16	·	·	·		**Main Macro Speed**
					000-127	Slow to Fast without Fade
					128-255	Slow to Fast with Fade
13	17	·	·	·	000-255	**Line_W CW** · 0% → 100%
14	18	·	·	·	000-255	**Line_W WW** · 0% → 100%
·	·	49	49	49	000-255	**Line_W CW 1** · 0% → 100%
·	·	50	50	50	000-255	**Line_W WW 1** · 0% → 100%
·	·	51	51	51	000-255	**Line_W CW 2** · 0% → 100%
·	·	52	52	52	000-255	**Line_W WW 2** · 0% → 100%
·	·	53	53	53	000-255	**Line_W CW 3** · 0% → 100%
·	·	54	54	54	000-255	**Line_W WW 3** · 0% → 100%
·	·	55	55	55	000-255	**Line_W CW 4** · 0% → 100%
·	·	56	56	56	000-255	**Line_W WW 4** · 0% → 100%
·	·	57	57	57	000-255	**Line_W CW 5** · 0% → 100%
·	·	58	58	58	000-255	**Line_W WW 5** · 0% → 100%
·	·	59	59	59	000-255	**Line_W CW 6** · 0% → 100%
·	·	60	60	60	000-255	**Line_W WW 6** · 0% → 100%
·	·	61	61	61	000-255	**Line_W CW 7** · 0% → 100%
·	·	62	62	62	000-255	**Line_W WW 7** · 0% → 100%
·	·	63	63	63	000-255	**Line_W CW 8** · 0% → 100%
·	·	64	64	64	000-255	**Line_W WW 8** · 0% → 100%
·	·	65	65	65	000-255	**Line_W CW 9** · 0% → 100%
·	·	66	66	66	000-255	**Line_W WW 9** · 0% → 100%
·	·	67	67	67	000-255	**Line_W CW 10** · 0% → 100%
·	·	68	68	68	000-255	**Line_W WW 10** · 0% → 100%
·	·	69	69	69	000-255	**Line_W CW 11** · 0% → 100%
·	·	70	70	70	000-255	**Line_W WW 11** · 0% → 100%
·	·	71	71	71	000-255	**Line_W CW 12** · 0% → 100%
·	·	72	72	72	000-255	**Line_W WW 12** · 0% → 100%
·	·	73	·	73	000-255	**Line_W CW 13** · 0% → 100%
·	·	74	·	74	000-255	**Line_W WW 13** · 0% → 100%

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
·	·	75	·	75	000-255	**Line_W CW 14** · 0% → 100%
·	·	76	·	76	000-255	**Line_W WW 14** · 0% → 100%
·	·	77	·	77	000-255	**Line_W CW 15** · 0% → 100%
·	·	78	·	78	000-255	**Line_W WW 15** · 0% → 100%
·	·	79	·	79	000-255	**Line_W CW 16** · 0% → 100%
·	·	80	·	80	000-255	**Line_W WW 16** · 0% → 100%
·	·	81	·	81	000-255	**Line_W CW 17** · 0% → 100%
·	·	82	·	82	000-255	**Line_W WW 17** · 0% → 100%
·	·	83	·	83	000-255	**Line_W CW 18** · 0% → 100%
·	·	84	·	84	000-255	**Line_W WW 18** · 0% → 100%
·	·	85	·	85	000-255	**Line_W CW 19** · 0% → 100%
·	·	86	·	86	000-255	**Line_W WW 19** · 0% → 100%
·	·	87	·	87	000-255	**Line_W CW 20** · 0% → 100%
·	·	88	·	88	000-255	**Line_W WW 20** · 0% → 100%
·	·	89	·	89	000-255	**Line_W CW 21** · 0% → 100%
·	·	90	·	90	000-255	**Line_W WW 21** · 0% → 100%
·	·	91	·	91	000-255	**Line_W CW 22** · 0% → 100%
·	·	92	·	92	000-255	**Line_W WW 22** · 0% → 100%
·	·	93	·	93	000-255	**Line_W CW 23** · 0% → 100%
·	·	94	·	94	000-255	**Line_W WW 23** · 0% → 100%
·	·	95	·	95	000-255	**Line_W CW 24** · 0% → 100%
·	·	96	·	96	000-255	**Line_W WW 24** · 0% → 100%
·	19	·	·	·		**Line_W CCT**
					000	Null
					001-004	Null
					005-009	Null
					010-013	Null
					014-018	Null
					019-022	Null
					023-027	Null
					028-031	Null
					032-036	Null
					037-040	Null
					041-045	Null
					046-049	Null
					050-054	Null
					055-058	Null
					059-063	Null
					064-067	Null
					068-072	6500K

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
					073-076	6400K
					077-081	6300K
					082-085	6200K
					086-090	6100K
					091-094	6000K
					095-099	5900K
					100-103	5800K
					104-108	5700K
					109-112	5600K
					113-117	5500K
					118-121	5400K
					122-126	5300K
					127-130	5200K
					131-135	5100K
					136-139	5000K
					140-144	4900K
					145-148	4800K
					149-153	4700K
					154-157	4600K
					158-162	4500K
					163-166	4400K
					167-171	4300K
					172-175	4200K
					176-180	4100K
					181-184	4000K
					185-189	3900K
					190-193	3800K
					194-198	3700K
					199-202	3600K
					203-207	3500K
					208-211	3400K
					212-216	3300K
					217-220	3200K
					221-225	3100K
					226-229	3000K
					230-234	2900K
					235-238	2800K
					239-243	2700K
					244-247	2600K
					248-255	Reserved Values
	20					**Line_W Macro**

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
					000-007	Null
					008-015	Built-in Effect 1
					016-023	Built-in Effect 2
					024-031	Built-in Effect 3
					032-039	Built-in Effect 4
					040-047	Built-in Effect 5
					048-055	Built-in Effect 6
					056-063	Built-in Effect 7
					064-071	Built-in Effect 8
					072-079	Built-in Effect 9
					080-087	Built-in Effect 10
					088-095	Built-in Effect 11
					096-103	Built-in Effect 12
					104-111	Built-in Effect 13
					112-119	Built-in Effect 14
					120-127	Built-in Effect 15
					128-135	Built-in Effect 16
					136-143	Built-in Effect 17
					144-151	Built-in Effect 18
					152-159	Built-in Effect 19
					160-167	Built-in Effect 20
					168-175	Built-in Effect 21
					176-183	Built-in Effect 22
					184-191	Built-in Effect 23
					192-199	Null
					200-207	Null
					208-215	Null
					216-223	Null
					224-231	Null
					232-239	Null
					240-247	Null
					248-255	Null
·	21	·	·	·		**Line_W Macro Speed**
					000-127	Slow to Fast without Fade
					128-255	Slow to Fast with Fade
15	22	97	·	·	000-255	**Line_RGB Red** · 0% → 100%
16	23	98	·	·	000-255	**Line_RGB Green** · 0% → 100%
17	24	99	·	·	000-255	**Line_RGB Blue** · 0% → 100%
·	·	·	73	97	000-255	**Line_RGB Red 1** · 0% → 100%
·	·	·	74	98	000-255	**Line_RGB Green 1** · 0% → 100%
·	·	·	75	99	000-255	**Line_RGB Blue 1** · 0% → 100%

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
·	·	·	76	100	000–255	**Line_RGB Red 2** · 0% → 100%
·	·	·	77	101	000–255	**Line_RGB Green 2** · 0% → 100%
·	·	·	78	102	000–255	**Line_RGB Blue 2** · 0% → 100%
·	·	·	79	103	000–255	**Line_RGB Red 3** · 0% → 100%
·	·	·	80	104	000–255	**Line_RGB Green 3** · 0% → 100%
·	·	·	81	105	000–255	**Line_RGB Blue 3** · 0% → 100%
·	·	·	82	106	000–255	**Line_RGB Red 4** · 0% → 100%
·	·	·	83	107	000–255	**Line_RGB Green 4** · 0% → 100%
·	·	·	84	108	000–255	**Line_RGB Blue 4** · 0% → 100%
·	·	·	85	109	000–255	**Line_RGB Red 5** · 0% → 100%
·	·	·	86	110	000–255	**Line_RGB Green 5** · 0% → 100%
·	·	·	87	111	000–255	**Line_RGB Blue 5** · 0% → 100%
·	·	·	88	112	000–255	**Line_RGB Red 6** · 0% → 100%
·	·	·	89	113	000–255	**Line_RGB Green 6** · 0% → 100%
·	·	·	90	114	000–255	**Line_RGB Blue 6** · 0% → 100%
·	·	·	91	115	000–255	**Line_RGB Red 7** · 0% → 100%
·	·	·	92	116	000–255	**Line_RGB Green 7** · 0% → 100%
·	·	·	93	117	000–255	**Line_RGB Blue 7** · 0% → 100%
·	·	·	94	118	000–255	**Line_RGB Red 8** · 0% → 100%
·	·	·	95	119	000–255	**Line_RGB Green 8** · 0% → 100%
·	·	·	96	120	000–255	**Line_RGB Blue 8** · 0% → 100%
·	·	·	97	121	000–255	**Line_RGB Red 9** · 0% → 100%
·	·	·	98	122	000–255	**Line_RGB Green 9** · 0% → 100%
·	·	·	99	123	000–255	**Line_RGB Blue 9** · 0% → 100%
·	·	·	100	124	000–255	**Line_RGB Red 10** · 0% → 100%
·	·	·	101	125	000–255	**Line_RGB Green 10** · 0% → 100%
·	·	·	102	126	000–255	**Line_RGB Blue 10** · 0% → 100%
·	·	·	103	127	000–255	**Line_RGB Red 11** · 0% → 100%
·	·	·	104	128	000–255	**Line_RGB Green 11** · 0% → 100%
·	·	·	105	129	000–255	**Line_RGB Blue 11** · 0% → 100%
·	·	·	106	130	000–255	**Line_RGB Red 12** · 0% → 100%
·	·	·	107	131	000–255	**Line_RGB Green 12** · 0% → 100%
·	·	·	108	132	000–255	**Line_RGB Blue 12** · 0% → 100%
·	·	·	·	133	000–255	**Line_RGB Red 13** · 0% → 100%
·	·	·	·	134	000–255	**Line_RGB Green 13** · 0% → 100%
·	·	·	·	135	000–255	**Line_RGB Blue 13** · 0% → 100%
·	·	·	·	136	000–255	**Line_RGB Red 14** · 0% → 100%
·	·	·	·	137	000–255	**Line_RGB Green 14** · 0% → 100%
·	·	·	·	138	000–255	**Line_RGB Blue 14** · 0% → 100%
·	·	·	·	139	000–255	**Line_RGB Red 15** · 0% → 100%

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
·	·	·	·	140	000-255	**Line_RGB Green 15** · 0% → 100%
·	·	·	·	141	000-255	**Line_RGB Blue 15** · 0% → 100%
·	·	·	·	142	000-255	**Line_RGB Red 16** · 0% → 100%
·	·	·	·	143	000-255	**Line_RGB Green 16** · 0% → 100%
·	·	·	·	144	000-255	**Line_RGB Blue 16** · 0% → 100%
·	·	·	·	145	000-255	**Line_RGB Red 17** · 0% → 100%
·	·	·	·	146	000-255	**Line_RGB Green 17** · 0% → 100%
·	·	·	·	147	000-255	**Line_RGB Blue 17** · 0% → 100%
·	·	·	·	148	000-255	**Line_RGB Red 18** · 0% → 100%
·	·	·	·	149	000-255	**Line_RGB Green 18** · 0% → 100%
·	·	·	·	150	000-255	**Line_RGB Blue 18** · 0% → 100%
·	·	·	·	151	000-255	**Line_RGB Red 19** · 0% → 100%
·	·	·	·	152	000-255	**Line_RGB Green 19** · 0% → 100%
·	·	·	·	153	000-255	**Line_RGB Blue 19** · 0% → 100%
·	·	·	·	154	000-255	**Line_RGB Red 20** · 0% → 100%
·	·	·	·	155	000-255	**Line_RGB Green 20** · 0% → 100%
·	·	·	·	156	000-255	**Line_RGB Blue 20** · 0% → 100%
·	·	·	·	157	000-255	**Line_RGB Red 21** · 0% → 100%
·	·	·	·	158	000-255	**Line_RGB Green 21** · 0% → 100%
·	·	·	·	159	000-255	**Line_RGB Blue 21** · 0% → 100%
·	·	·	·	160	000-255	**Line_RGB Red 22** · 0% → 100%
·	·	·	·	161	000-255	**Line_RGB Green 22** · 0% → 100%
·	·	·	·	162	000-255	**Line_RGB Blue 22** · 0% → 100%
·	·	·	·	163	000-255	**Line_RGB Red 23** · 0% → 100%
·	·	·	·	164	000-255	**Line_RGB Green 23** · 0% → 100%
·	·	·	·	165	000-255	**Line_RGB Blue 23** · 0% → 100%
·	·	·	·	166	000-255	**Line_RGB Red 24** · 0% → 100%
·	·	·	·	167	000-255	**Line_RGB Green 24** · 0% → 100%
·	·	·	·	168	000-255	**Line_RGB Blue 24** · 0% → 100%
·	25	·	·	·		**Line_RGB Color**
					000-007	Null
					008-015	Color 1
					016-023	Color 2
					024-031	Color 3
					032-039	Color 4
					040-047	Color 5
					048-055	Color 6
					056-063	Color 7
					064-071	Color 8
					072-079	Color 9

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
					080-087	Color 10
					088-095	Color 11
					096-103	Color 12
					104-111	Color 13
					112-119	Color 14
					120-127	Color 15
					128-135	Color 16
					136-143	Color 17
					144-151	Color 18
					152-159	Color 19
					160-167	Color 20
					168-175	Color 21
					176-183	Color 22
					184-191	Color 23
					192-199	Color 24
					200-207	Color 25
					208-215	Color 26
					216-223	Color 27
					224-231	Color 28
					232-239	Color 29
					240-247	Color 30
					248-255	Color 31
	26					**Line_RGB Macro**
					000-007	Null
					008-015	Built-in Effect 1
					016-023	Built-in Effect 2
					024-031	Built-in Effect 3
					032-039	Built-in Effect 4
					040-047	Built-in Effect 5
					048-055	Built-in Effect 6
					056-063	Built-in Effect 7
					064-071	Built-in Effect 8
					072-079	Built-in Effect 9
					080-087	Built-in Effect 10
					088-095	Built-in Effect 11
					096-103	Built-in Effect 12
					104-111	Built-in Effect 13
					112-119	Built-in Effect 14
					120-127	Built-in Effect 15
					128-135	Built-in Effect 16
					136-143	Built-in Effect 17

17CH	27CH	99CH	108CH	168CH	VALUE	FUNCTION
					144-151	Built-in Effect 18
					152-159	Built-in Effect 19
					160-167	Built-in Effect 20
					168-175	Built-in Effect 21
					176-183	Built-in Effect 22
					184-191	Built-in Effect 23
					192-199	Null
					200-207	Null
					208-215	Null
					216-223	Null
					224-231	Null
					232-239	Null
					240-247	Null
					248-255	Null
	27					**Line_RGB Macro Speed**
					000-127	Slow to Fast without Fade
					128-255	Slow to Fast with Fade

Mode 6-7: Controlled by DMX (8+100ch / 8+160ch)

8+100CH (MODE 6)	8+160CH (MODE 7)	VALUE	FUNCTION
1	1	000-255	**Tilt** · 0° → 202°
2	2	000-255	**Tilt Fine**
3	3	000-255	**Zoom** · Wide → Narrow
4	4	000-255	**Dimmer** · 0% → 100%
5	5		**Main Strobe**
		000-007	Close
		008-015	Open
		016-131	Strobe from Slow to Fast
		132-139	Open
		140-181	Slow Open Fast Close from Slow to Fast
		182-189	Open
		190-231	Fast Open Slow Close from Slow to Fast
		232-239	Open
		240-247	Random Strobe from Slow to Fast
		248-255	Open
6	6		**Line_W Strobe**
		000-007	Close
		008-015	Open
		016-131	Strobe from Slow to Fast
		132-139	Open
		140-181	Slow Open Fast Close from Slow to Fast

8+100CH (MODE 6)	8+160CH (MODE 7)	VALUE	FUNCTION
		182-189	Open
		190-231	Fast Open Slow Close from Slow to Fast
		232-239	Open
		240-247	Random Strobe from Slow to Fast
		248-255	Open
7	7		**Line_RGB Strobe**
		000-007	Close
		008-015	Open
		016-131	Strobe from Slow to Fast
		132-139	Open
		140-181	Slow Open Fast Close from Slow to Fast
		182-189	Open
		190-231	Fast Open Slow Close from Slow to Fast
		232-239	Open
		240-247	Random Strobe from Slow to Fast
		248-255	Open
8	8		**Special Function**
		000-029	Null
		030-039	Dimmer Curve: Linear
		040-049	Dimmer Curve: Square Law
		050-059	Dimmer Curve: Inv SQ Law
		060-069	Dimmer Curve: S Curve
		070-079	Power Mode: Standard
		080-089	Null
		090-099	Power Mode: Quiet
		100-109	Led Frequency Setting Enable
		110-119	Led Frequency Setting Disable
		120-122	Null
		123	900Hz
		124	1000Hz
		125	1100Hz
		126	1200Hz
		127	1300Hz
		128	1400Hz
		129	1500Hz
		130	2500Hz
		131	4000Hz
		132	5000Hz
		133	6000Hz
		134	10KHz

8+100CH (MODE 6)	8+160CH (MODE 7)	VALUE	FUNCTION
		135	15KHz
		136	20KHz
		137	25KHz
		138-139	Null
		140-149	Tilt Reset
		150-159	Effect Reset
		160-169	CCT Calibration: On
		170-179	CCT Calibration: Off
		180-189	Invert Pixel Order: No
		190-199	Invert Pixel Order: Yes
		200-209	All Reset
		210-219	Dimmer Speed: Fast
		220-229	Dimmer Speed: Smooth
		230-239	Line Power Mode: Off
		240-249	Line Power Mode: On
		250-251	Dimming Start Mode: High
		252-253	Dimming Start Mode: Low
		254-255	Null

Mode 6-7: Controlled by Art-Net (8+100ch / 8+160ch)

8+100CH ART-NET (MODE 6)	8+160CH ART-NET (MODE 7)	VALUE	FUNCTION
1	1	000-255	**Main Red 1** · 0% → 100%
2	2	000-255	**Main Green 1** · 0% → 100%
3	3	000-255	**Main Blue 1** · 0% → 100%
4	4	000-255	**Main White 1** · 0% → 100%
5	5	000-255	**Main Red 2** · 0% → 100%
6	6	000-255	**Main Green 2** · 0% → 100%
7	7	000-255	**Main Blue 2** · 0% → 100%
8	8	000-255	**Main White 2** · 0% → 100%
9	9	000-255	**Main Red 3** · 0% → 100%
10	10	000-255	**Main Green 3** · 0% → 100%
11	11	000-255	**Main Blue 3** · 0% → 100%
12	12	000-255	**Main White 3** · 0% → 100%
13	13	000-255	**Main Red 4** · 0% → 100%
14	14	000-255	**Main Green 4** · 0% → 100%
15	15	000-255	**Main Blue 4** · 0% → 100%
16	16	000-255	**Main White 4** · 0% → 100%
17	17	000-255	**Main Red 5** · 0% → 100%
18	18	000-255	**Main Green 5** · 0% → 100%

8+100CH ART-NET (MODE 6)	8+160CH ART-NET (MODE 7)	VALUE	FUNCTION
19	19	000–255	**Main Blue 5** · 0% → 100%
20	20	000–255	**Main White 5** · 0% → 100%
21	21	000–255	**Main Red 6** · 0% → 100%
22	22	000–255	**Main Green 6** · 0% → 100%
23	23	000–255	**Main Blue 6** · 0% → 100%
24	24	000–255	**Main White 6** · 0% → 100%
25	25	000–255	**Main Red 7** · 0% → 100%
26	26	000–255	**Main Green 7** · 0% → 100%
27	27	000–255	**Main Blue 7** · 0% → 100%
28	28	000–255	**Main White 7** · 0% → 100%
29	29	000–255	**Main Red 8** · 0% → 100%
30	30	000–255	**Main Green 8** · 0% → 100%
31	31	000–255	**Main Blue 8** · 0% → 100%
32	32	000–255	**Main White 8** · 0% → 100%
33	33	000–255	**Main Red 9** · 0% → 100%
34	34	000–255	**Main Green 9** · 0% → 100%
35	35	000–255	**Main Blue 9** · 0% → 100%
36	36	000–255	**Main White 9** · 0% → 100%
37	37	000–255	**Main Red 10** · 0% → 100%
38	38	000–255	**Main Green 10** · 0% → 100%
39	39	000–255	**Main Blue 10** · 0% → 100%
40	40	000–255	**Main White 10** · 0% → 100%
41	41	000–255	**Line_W CW 1** · 0% → 100%
42	42	000–255	**Line_W WW 1** · 0% → 100%
43	43	000–255	**Line_W CW 2** · 0% → 100%
44	44	000–255	**Line_W WW 2** · 0% → 100%
45	45	000–255	**Line_W CW 3** · 0% → 100%
46	46	000–255	**Line_W WW 3** · 0% → 100%
47	47	000–255	**Line_W CW 4** · 0% → 100%
48	48	000–255	**Line_W WW 4** · 0% → 100%
49	49	000–255	**Line_W CW 5** · 0% → 100%
50	50	000–255	**Line_W WW 5** · 0% → 100%
51	51	000–255	**Line_W CW 6** · 0% → 100%
52	52	000–255	**Line_W WW 6** · 0% → 100%
53	53	000–255	**Line_W CW 7** · 0% → 100%
54	54	000–255	**Line_W WW 7** · 0% → 100%
55	55	000–255	**Line_W CW 8** · 0% → 100%
56	56	000–255	**Line_W WW 8** · 0% → 100%

8+100CH ART-NET (MODE 6)	8+160CH ART-NET (MODE 7)	VALUE	FUNCTION
57	57	000-255	**Line_W CW 9** · 0% → 100%
58	58	000-255	**Line_W WW 9** · 0% → 100%
59	59	000-255	**Line_W CW 10** · 0% → 100%
60	60	000-255	**Line_W WW 10** · 0% → 100%
61	61	000-255	**Line_W CW 11** · 0% → 100%
62	62	000-255	**Line_W WW 11** · 0% → 100%
63	63	000-255	**Line_W CW 12** · 0% → 100%
64	64	000-255	**Line_W WW 12** · 0% → 100%
·	65	000-255	**Line_W CW 13** · 0% → 100%
·	66	000-255	**Line_W WW 13** · 0% → 100%
·	67	000-255	**Line_W CW 14** · 0% → 100%
·	68	000-255	**Line_W WW 14** · 0% → 100%
·	69	000-255	**Line_W CW 15** · 0% → 100%
·	70	000-255	**Line_W WW 15** · 0% → 100%
·	71	000-255	**Line_W CW 16** · 0% → 100%
·	72	000-255	**Line_W WW 16** · 0% → 100%
·	73	000-255	**Line_W CW 17** · 0% → 100%
·	74	000-255	**Line_W WW 17** · 0% → 100%
·	75	000-255	**Line_W CW 18** · 0% → 100%
·	76	000-255	**Line_W WW 18** · 0% → 100%
·	77	000-255	**Line_W CW 19** · 0% → 100%
·	78	000-255	**Line_W WW 19** · 0% → 100%
·	79	000-255	**Line_W CW 20** · 0% → 100%
·	80	000-255	**Line_W WW 20** · 0% → 100%
·	81	000-255	**Line_W CW 21** · 0% → 100%
·	82	000-255	**Line_W WW 21** · 0% → 100%
·	83	000-255	**Line_W CW 22** · 0% → 100%
·	84	000-255	**Line_W WW 22** · 0% → 100%
·	85	000-255	**Line_W CW 23** · 0% → 100%
·	86	000-255	**Line_W WW 23** · 0% → 100%
·	87	000-255	**Line_W CW 24** · 0% → 100%
·	88	000-255	**Line_W WW 24** · 0% → 100%
65	89	000-255	**Line_RGB Red 1** · 0% → 100%
66	90	000-255	**Line_RGB Green 1** · 0% → 100%
67	91	000-255	**Line_RGB Blue 1** · 0% → 100%
68	92	000-255	**Line_RGB Red 2** · 0% → 100%
69	93	000-255	**Line_RGB Green 2** · 0% → 100%
70	94	000-255	**Line_RGB Blue 2** · 0% → 100%

8+100CH ART-NET (MODE 6)	8+160CH ART-NET (MODE 7)	VALUE	FUNCTION
71	95	000-255	**Line_RGB Red 3** · 0% → 100%
72	96	000-255	**Line_RGB Green 3** · 0% → 100%
73	97	000-255	**Line_RGB Blue 3** · 0% → 100%
74	98	000-255	**Line_RGB Red 4** · 0% → 100%
75	99	000-255	**Line_RGB Green 4** · 0% → 100%
76	100	000-255	**Line_RGB Blue 4** · 0% → 100%
77	101	000-255	**Line_RGB Red 5** · 0% → 100%
78	102	000-255	**Line_RGB Green 5** · 0% → 100%
79	103	000-255	**Line_RGB Blue 5** · 0% → 100%
80	104	000-255	**Line_RGB Red 6** · 0% → 100%
81	105	000-255	**Line_RGB Green 6** · 0% → 100%
82	106	000-255	**Line_RGB Blue 6** · 0% → 100%
83	107	000-255	**Line_RGB Red 7** · 0% → 100%
84	108	000-255	**Line_RGB Green 7** · 0% → 100%
85	109	000-255	**Line_RGB Blue 7** · 0% → 100%
86	110	000-255	**Line_RGB Red 8** · 0% → 100%
87	111	000-255	**Line_RGB Green 8** · 0% → 100%
88	112	000-255	**Line_RGB Blue 8** · 0% → 100%
89	113	000-255	**Line_RGB Red 9** · 0% → 100%
90	114	000-255	**Line_RGB Green 9** · 0% → 100%
91	115	000-255	**Line_RGB Blue 9** · 0% → 100%
92	116	000-255	**Line_RGB Red 10** · 0% → 100%
93	117	000-255	**Line_RGB Green 10** · 0% → 100%
94	118	000-255	**Line_RGB Blue 10** · 0% → 100%
95	119	000-255	**Line_RGB Red 11** · 0% → 100%
96	120	000-255	**Line_RGB Green 11** · 0% → 100%
97	121	000-255	**Line_RGB Blue 11** · 0% → 100%
98	122	000-255	**Line_RGB Red 12** · 0% → 100%
99	123	000-255	**Line_RGB Green 12** · 0% → 100%
100	124	000-255	**Line_RGB Blue 12** · 0% → 100%
·	125	000-255	**Line_RGB Red 13** · 0% → 100%
·	126	000-255	**Line_RGB Green 13** · 0% → 100%
·	127	000-255	**Line_RGB Blue 13** · 0% → 100%
·	128	000-255	**Line_RGB Red 14** · 0% → 100%
·	129	000-255	**Line_RGB Green 14** · 0% → 100%
·	130	000-255	**Line_RGB Blue 14** · 0% → 100%
·	131	000-255	**Line_RGB Red 15** · 0% → 100%
·	132	000-255	**Line_RGB Green 15** · 0% → 100%

8+100CH ART-NET (MODE 6)	8+160CH ART-NET (MODE 7)	VALUE	FUNCTION
·	133	000-255	**Line_RGB Blue 15** · 0% → 100%
·	134	000-255	**Line_RGB Red 16** · 0% → 100%
·	135	000-255	**Line_RGB Green 16** · 0% → 100%
·	136	000-255	**Line_RGB Blue 16** · 0% → 100%
·	137	000-255	**Line_RGB Red 17** · 0% → 100%
·	138	000-255	**Line_RGB Green 17** · 0% → 100%
·	139	000-255	**Line_RGB Blue 17** · 0% → 100%
·	140	000-255	**Line_RGB Red 18** · 0% → 100%
·	141	000-255	**Line_RGB Green 18** · 0% → 100%
·	142	000-255	**Line_RGB Blue 18** · 0% → 100%
·	143	000-255	**Line_RGB Red 19** · 0% → 100%
·	144	000-255	**Line_RGB Green 19** · 0% → 100%
·	145	000-255	**Line_RGB Blue 19** · 0% → 100%
·	146	000-255	**Line_RGB Red 20** · 0% → 100%
·	147	000-255	**Line_RGB Green 20** · 0% → 100%
·	148	000-255	**Line_RGB Blue 20** · 0% → 100%
·	149	000-255	**Line_RGB Red 21** · 0% → 100%
·	150	000-255	**Line_RGB Green 21** · 0% → 100%
·	151	000-255	**Line_RGB Blue 21** · 0% → 100%
·	152	000-255	**Line_RGB Red 22** · 0% → 100%
·	153	000-255	**Line_RGB Green 22** · 0% → 100%
·	154	000-255	**Line_RGB Blue 22** · 0% → 100%
·	155	000-255	**Line_RGB Red 23** · 0% → 100%
·	156	000-255	**Line_RGB Green 23** · 0% → 100%
·	157	000-255	**Line_RGB Blue 23** · 0% → 100%
·	158	000-255	**Line_RGB Red 24** · 0% → 100%
·	159	000-255	**Line_RGB Green 24** · 0% → 100%
·	160	000-255	**Line_RGB Blue 24** · 0% → 100%

Mode 8 (21ch)

21CH	VALUE	FUNCTION
1	000-255	**Tilt** · 0° → 202°
2	000-255	**Tilt Fine**
3	000-255	**Zoom** · Wide → Narrow
4	000-255	**Dimmer** · 0% → 100%
5		**Main Strobe**
	000-007	Close
	008-015	Open
	016-131	Strobe from Slow to Fast

21CH	VALUE	FUNCTION
	132-139	Open
	140-181	Slow Open Fast Close from Slow to Fast
	182-189	Open
	190-231	Fast Open Slow Close from Slow to Fast
	232-239	Open
	240-247	Random Strobe from Slow to Fast
	248-255	Open
6		**Line_W Strobe**
	000-007	Close
	008-015	Open
	016-131	Strobe from Slow to Fast
	132-139	Open
	140-181	Slow Open Fast Close from Slow to Fast
	182-189	Open
	190-231	Fast Open Slow Close from Slow to Fast
	232-239	Open
	240-247	Random Strobe from Slow to Fast
	248-255	Open
7		**Line_RGB Strobe**
	000-007	Close
	008-015	Open
	016-131	Strobe from Slow to Fast
	132-139	Open
	140-181	Slow Open Fast Close from Slow to Fast
	182-189	Open
	190-231	Fast Open Slow Close from Slow to Fast
	232-239	Open
	240-247	Random Strobe from Slow to Fast
	248-255	Open
8		**Special Function**
	000-029	Null
	030-039	Dimmer Curve: Linear
	040-049	Dimmer Curve: Square Law
	050-059	Dimmer Curve: Inv SQ Law
	060-069	Dimmer Curve: S Curve
	070-079	Power Mode: Standard
	080-089	Null
	090-099	Power Mode: Quiet
	100-109	Led Frequency Setting Enable
	110-119	Led Frequency Setting Disable
	120-122	Null

21CH	VALUE	FUNCTION
	123	900Hz
	124	1000Hz
	125	1100Hz
	126	1200Hz
	127	1300Hz
	128	1400Hz
	129	1500Hz
	130	2500Hz
	131	4000Hz
	132	5000Hz
	133	6000Hz
	134	10KHz
	135	15KHz
	136	20KHz
	137	25KHz
	138-139	Null
	140-149	Tilt Reset
	150-159	Effect Reset
	160-169	CCT Calibration: On
	170-179	CCT Calibration: Off
	180-189	Invert Pixel Order: No
	190-199	Invert Pixel Order: Yes
	200-209	All Reset
	210-219	Dimmer Speed: Fast
	220-229	Dimmer Speed: Smooth
	230-239	Line Power Mode: Off
	240-249	Line Power Mode: On
	250-251	Dimming Start Mode: High
	252-253	Dimming Start Mode: Low
	254-255	Null
9	000-255	**Main Red** · 0% → 100%
10	000-255	**Main Green** · 0% → 100%
11	000-255	**Main Blue** · 0% → 100%
12	000-255	**Main White** · 0% → 100%
13	000-255	**Line_W CW** · 0% → 100%
14	000-255	**Line_W WW** · 0% → 100%
15	000-255	**Line_RGB Red** · 0% → 100%
16	000-255	**Line_RGB Green** · 0% → 100%
17	000-255	**Line_RGB Blue** · 0% → 100%
18	000-255	**Main Red 11&12** · 0% → 100%
19	000-255	**Main Green 11&12** · 0% → 100%

21CH	VALUE	FUNCTION
20	000-255	**Main Blue 11&12** · 0% → 100%
21	000-255	**Main White 11&12** · 0% → 100%

※ Special Function channel: to activate the listed functions, stop in DMX value for at least 3 seconds.

※ Modes 6-7 (8+100ch / 8+160ch) split control: the first 8 channels are controlled by DMX, the pixel data by Art-Net (separate address spaces, each numbered from 1).