DMX CHART

Event Lighting Fresnel F48VW

Model F48VW · Prepared by Krank'd · krankd.com.au

Hire this fixture from Krank'd

1ch 1U 2ch 5ch 7ch

1 channel mode

1CH	VALUE	FUNCTION
1	000-255	**Dimmer & Colour temperature**

1U mode

1U	VALUE	FUNCTION
1	000-255	**Dimmer** · Dimmer (dim the preset color selected in Menu)

2 channel mode

2CH	VALUE	FUNCTION
1	000-255	**Dimmer** · Dimmer 0% ~ 100%
2	000-255	**Colour temperature** · Warm white to cool white

5 channel mode

5CH	VALUE	FUNCTION
1	000-255	**Master dimmer coarse** · Master dimmer coarse: 0% ~ 100%
2	000-255	**Master dimmer fine** · Master dimmer fine: 0% ~ 100%
3	000-255	**Colour temperature** · Warm white to cool white
4		**Strobe**
	000-015	No function(Shutter on)
	016-119	Strobe slow to fast (1-25Hz)
	120-127	Shutter on
	128-183	Strobe random slow to fast
	184-191	Shutter on
	192-247	Strobe audio sensitivity low to high
	248-255	Shutter on
5		**Fade mode (DMX delay)**
	000-050	Standard
	051-101	Stage
	102-152	TV
	153-203	Architect
	204-255	Theater

7 channel mode

7CH	VALUE	FUNCTION
1	000-255	**Master dimmer coarse** · Master dimmer coarse: 0% ~ 100%
2	000-255	**Master dimmer fine** · Master dimmer fine: 0% ~ 100%
3	000-255	**Warm White**
4	000-255	**Cool White**
5		**Strobe**

7CH	VALUE	FUNCTION
	000-015	No function(Shutter on)
	016-119	Strobe slow to fast (1-25Hz)
	120-127	Shutter on
	128-183	Strobe random slow to fast
	184-191	Shutter on
	192-247	Strobe audio sensitivity low to high
	248-255	Shutter on
6		**Preset Colours**
	000-009	No function
	010-255	Preset Colours (Warm->Cold)
7		**Fade mode (DMX delay)**
	000-050	Standard
	051-101	Stage
	102-152	TV
	153-203	Architect
	204-255	Theater

※ No F48VW manual could be found, so this chart is taken from the manual for the Event Lighting F96VW. Check the modes on your fixture's menu before patching.

※ That manual's menu and specifications list 1, 2 and 5 channel modes, but it also prints a 7 channel table; every table is shown here as printed.

※ The 1U mode's channel is printed as "1U" in the source (a dimmer-only variant of 1-channel mode); the DMX channel offset is 1.