DMX CHART

Fusion Wash Q48

Model ShowPRO LEDWSH480 · Prepared by Krank'd · krankd.com.au

Hire this fixture from Krank'd

4ch 6ch 10ch 16ch

4CH

4CH	VALUE	FUNCTION
1	000–255	**Red** · 0~100%
2	000–255	**Green** · 0~100%
3	000–255	**Blue** · 0~100%
4	000–255	**White** · 0~100%

6CH

6CH	VALUE	FUNCTION
1	000–255	**Dimmer** · 0~100%
2	000–255	**Red** · 0~100%
3	000–255	**Green** · 0~100%
4	000–255	**Blue** · 0~100%
5	000–255	**White** · 0~100%
6		**Strobe**
	000–010	NO Function
	011–255	Strobe Slow to Fast

10CH

10CH	VALUE	FUNCTION
1	000–255	**Dimmer** · 0~100%
2	000–255	**Red** · 0~100%
3	000–255	**Green** · 0~100%
4	000–255	**Blue** · 0~100%
5	000–255	**White** · 0~100%
6		**Strobe**
	000–010	No function
	011–255	Strobe slow to fast
7		**Color Macro**
	000–010	No Function
	011–030	R 100%, G 0~100%, B 0%
	031–050	R 100%~0%, G 100%, B 0%
	051–070	R 0%, G 100%, B 0~100%
	071–090	R 0%, G 100%~0%, B 100%
	091–110	R 0%~100%, G 0%, B 100%
	111–130	R 100%, G 0%, B 100%~0%
	131–150	R 100%, G 0%~100%, B 0%~100%
	151–170	R 100%~0%, G 100%~0%, B 100%
	171–200	R 100%, G 100%, B 100%, W 100%

10CH	VALUE	FUNCTION
	201-205	Color 1
	206-210	Color 2
	211-215	Color 3
	216-220	Color 4
	221-225	Color 5
	226-230	Color 6
	231-235	Color 7
	236-240	Color 8
	241-245	Color 9
	246-250	Color 10
	251-255	Color 11
8		**Effects**
	000-010	No Function
	011-037	Effect 1
	038-064	Effect 2
	065-091	Effect 3
	092-118	Effect 4
	119-145	Effect 5 (Effects 1- 4)
	146-172	Effect 6
	173-199	Effect 7
	200-226	Effect 8
	227-255	Effect 9 (Effects 6- 8)
9	000-255	**Effects speed** · Effects speed slow to fast
10		**Dimmer Speed Mode**
	000-051	Preset dimmer speed from display menu
	052-101	Dimmer speed mode off
	102-152	Dimmer speed mode 1 (fast speed)
	153-203	Dimmer speed mode 2 (middle speed)
	204-255	Dimmer speed mode 3 (slow speed)

16CH

16CH	VALUE	FUNCTION
1	000-255	**Red 1** · 0~100%
2	000-255	**Green 1** · 0~100%
3	000-255	**Blue 1** · 0~100%
4	000-255	**White 1** · 0~100%
5	000-255	**Red 2** · 0~100%
6	000-255	**Green 2** · 0~100%
7	000-255	**Blue 2** · 0~100%
8	000-255	**White 2** · 0~100%
9	000-255	**Red 3** · 0~100%
10	000-255	**Green 3** · 0~100%

16CH	VALUE	FUNCTION
11	000–255	**Blue 3** · 0~100%
12	000–255	**White 3** · 0~100%
13	000–255	**Red 4** · 0~100%
14	000–255	**Green 4** · 0~100%
15	000–255	**Blue 4** · 0~100%
16	000–255	**White 4** · 0~100%

※ Per §3.10: 4-channel = Basic RGBW dimming; 6-channel = Basic RGBW dimming + master dimmer + strobe; 10-channel = colour and effect macros + dimmer curve selection; 16-channel = RGBW control of 4 independent horizontal rows.